

1302nm PM Bandpass Filter for Pulse Power

FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



SPECIFICATIONS

Parameters		Unit	Standard	High ER Type
Center Wavelength		nm	1302	
Min. Pass Band Width @ 0.5dB		nm	16.0	
Insertion Loss over Pass Band Wavelength		dB	≤1.0	≤1.2
Stop Wavelength (ASE)		nm	1250~1290 & 1314-1410	
Stop Wavelength (ASE)	Standard	dB	≥25	
Isolation	High Isolation	dB	≥45	
ASE Direction		-	F: Forward, B: Backward, T: Two-way	
Configuration		-	D: 2-port, Y: 3-port, X: 4-port	
Optical Return Loss		dB	≥50	
Extinction Ratio		dB	≥18	≥20
Fiber Type	Input&Output	-	PM1310 Panda Fiber or 10/125um PMDC Fiber NA=0.08 (O)	
			10/130um PMDC Fiber NA=0.15 (O2) or 12/130um PMDC Fiber (T)	
			25/250um PMDC Fiber (R) or 25/300um PMDC Fiber (G)	
	ASE Guide Out (Y/X Type)	-	Same Fiber, Corr. SM Fiber or MM Fiber	
Fiber Tensile Load		N	5	
Max. Average Optical Power (ASE+Signal)		W	0.3, 0.5, 1, 2, 3, 5, 10, 15, 20, 30, 50, 60, 80, 100	
Max. Peak Power for pulse		kW	0.1, 1, 2, 3, 5, 10, 15, 20	
Max. ASE Average Power		W	0.3, 0.5, 1, 2, 3, 4, 5, 10	
Operating Temperature		°C	0~70	
Storage Temperature		°C	-40~85	
Package Dimension	Stainless Steel Tube (SST)	mm	∅5.5x ^L 35 (≤5W); ∅6.0x ^L 50(5~10W)	
	Metal Box	mm	H: ^L 90x ^W 12x ^H 10 (>10W); M: ^L 120x ^W 12x ^H 10 (≤10W)	

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
 - To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 - High ER type can only work in slow axis; Suggest to use Y/X type or H Box if blocked optical power is ≥1W.
 - Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
 - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 - Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

FPBP-1302-NNN(C)(C) (C)-(C) (C) -H NN P NN -(NN) - (C) C C NN - CC/CC

Bandwidth	Type	ASE Type	ASE Iso	Fwd ASE Fiber	Bwd ASE Fiber	Average Power	Peak Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
160-16nm	R=High ER	B=Backward	I=High	Y=Same Fiber	Y=Same Fiber	03-300mW	01-100W	1- 1W	M= Metal Box	2-PM1310Fiber	B= Bare fiber	05-0.5m	N=Without Connector
	Blank for	T=Two-way	Isolation	S=Corr. SM Fiber	S=Corr. SM Fiber	1- 1W	1- 1kW	5- 5W	H=H Box	0=10/125 PMDC Fiber	L= Loose Tube	10-1.0m	FC/APC=FC/APC Connector
	Standard	Blank for Forward	Blank for	N=None	A=105/125um Fiber	5- 5W	10- 10kW	10-10W	Blank for SST	T=12/130 PMDC Fiber	2- 2mm Cable	15-1.5m	LC/PC=LC/PC Connector
		Standard	Blank for D Type	Blank for D Type	Blank for None or D Type	20-20W	20-20kW	Blank for 300mW		G=25/300 PMDC Fiber	3- 3mm Cable	20-2.0m	SC/UPC=SC/UPC Connector

