

Optical Filter Coupler

FEATURES

- ▣ Low Excess Loss
- ▣ Various Splitting Ratio
- ▣ Wide Passband
- ▣ High Stability and Reliability
- ▣ Epoxy Free Optical Path

APPLICATIONS

- ▣ Optical Amplifier
- ▣ Optical Networks
- ▣ Power Monitoring
- ▣ Fiber Sensor
- ▣ Lab



SPECIFICATIONS

Parameter	Unit	1x2 Type			2x2 Type		
Center Wavelength	nm	1310, 1480, 1550, 1590					
Bandwidth	nm	+/-40 or customer specify					
Split Ratio	-	1:99	2:98	5:95	10:90	40:60	50:50
Tap Ratio	-	1±0.5%	2±0.6%	5±1.0%	10%	40%	50%
Excess Loss	Max.	dB			0.8		
Uniformity	Max.	dB			0.6		
PDL	dB	≤0.1					
Optical Return Loss	dB	≥50					
Fiber Type	Tap Port	- Same Fiber or 50/125um MM Fiber					
	Thru Port	- SMF-28 Fiber or 10/130um DC Fiber (O) 12/130um DC Fiber (T) or 20/130um DC Fiber (Q) 25/250um DC Fiber (R) or 25/300um DC Fiber (G)					
Fiber Tensile Load	N	5					
Max. Optical Power (CW)	mW	300					
Operating Temperature	°C	0~70					
Storage Temperature	°C	-40~85					
Package	Stainless Steel Tube (SST)	mm	∅5.5x ^L 35				
Dimension	Metal Box	mm	^L 120x ^W 12x ^H 10				

- Note:** 1. Specifications are for device without connectors; Specifications may change without notice.
 2. To add connectors, IL is 0.3dB higher, RL is 5dB lower.
 3. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

ORDERING INFORMATION (PN)

FFFC - NNNN - NN	N	(C)	-(C)	(C)	C	NN	- CC/CCC	
Wavelength	Split Ratio	Type	Tap Port Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1310-1310nm	01-1/99	1-1x2 Type	S-50/125um Fiber	M-Metal Box	O-10/130 DC Fiber	B- Bare fiber	05-0.5m	N-Without Connector
1480-1480nm	05-5/95	2-2x2 Type	Blank for Same Fiber	Blank for SST	T-12/130 DC Fiber	L- Loose Tube	10-1.0m	FC/APC-FC/APC Connector
1550-1550nm	10-10/90				R-25/250 DC Fiber	2- 2mm Cable	15-1.5m	LC/PC-LC/PC Connector
1590-1590nm	50-50/50				Blank for SMF-28 Fiber	3- 3mm Cable	20-2.0m	SC/UPC-SC/UPC Connector