

## 1970nm PM Bandpass Filter/Isolator Hybrid

### FEATURES

- High Isolation
- Low Insertion Loss
- Various Bandwidth
- High Reliability and Stability
- Compact Package

### APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Research Labs
- Laser System



### SPECIFICATIONS

Parameters	Unit	Single Stage	Dual Stage
Center Wavelength	nm	1970	
Min. Pass Band Width @ 0.5dB	nm	6.0	
Stop Band @ 25dB	nm	1900-1960 & 1980-2050	
Insertion Loss@23°C	dB	≤1.6	≤1.9
Signal Isolation (23°C)	dB	≥16	≥30
Configuration	D Type	-	2-port
	Y Type	-	3-port, (Blocked Wavelength Guide Out)
	X Type	-	4-port, (Both Block Wavelength Guide Out)
Fiber Type at 3 <sup>rd</sup> or 4 <sup>th</sup> Port (Y/X Type)	-	Same Fiber, Corr. SM Fiber or 50/125um MM Fiber	
ASE Direction	Forward Type	-	Bandpass Filter is before isolator
	Backward Type	-	Bandpass Filter is after isolator
	Twin Type	-	Bandpass Filter is at both sides of isolator
Optical Return Loss	dB	≥45	
Extinction Ratio	dB	≥18	
Work Mode	S Type	-	Can only work in slow axis
	F Type	-	Can work both in slow axis and fast axis
Fiber Type	-	PM1550 Panda Fiber or PM1950 Fiber (V) 10/130um PMDC Fiber (O) or 25/250um PMDC Fiber (R)	
Max. Optical Power (CW)	mW	300	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package	Stainless Steel Tube (SST)	mm	(Ø)5.5x35
Dimension	Metal Box	mm	(L)120x(W)12x(H)10

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
  2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  3. Suggest to use Y or X type if blocked optical power is >1W.
  4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

### ORDERING INFORMATION (PN)

Stage	Bandwidth	ASE Type	Work Mode	3rd Port Fiber	4th Port Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
S= Single Stage	60~6nm	F= Forward	S= S Type	Y=Same Fiber	Y=Same Fiber	M=Metal Box	2=PM1550Fiber	B= Bare fiber	05=0.5m	N=Without Connector
D= Dual Stage		B=Backward	F= F Type	S=Corr. SM Fiber	S=Corr. SM Fiber	Blank for SST	V=PM1950 Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
		T=Twin		5=50/125um Fiber	5=50/125um Fiber		O=10/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
				Blank for D Type	Blank for D&Y Type		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector

