

1078nm Multimode Bandpass Filter

FEATURES

- ▣ High Isolation
- ▣ Low Insertion Loss
- ▣ High Reliability and Stability
- ▣ Various Bandwidth
- ▣ High Optical Power

APPLICATIONS

- ▣ Broadband Systems
- ▣ Optical Amplifying Systems
- ▣ Telecommunication Networks
- ▣ Laser Systems
- ▣ Research Labs



SPECIFICATIONS

Parameters		Unit	Value
Center Wavelength		nm	1078
Min. Pass Band Width @ 0.5dB		nm	9.0
Insertion Loss over Pass Band Wavelength		dB	≤1.2
Stop Wavelength (ASE)		nm	1000~1069&1087~1120
Stop Wavelength (ASE)	Standard	dB	≥25
Isolation	High Isolation	dB	≥45
ASE Direction		-	F: Forward, B: Backward, T: Two-way
Configuration		-	D: 2-port, Y: 3-port, X: 4-port
Optical Return Loss		dB	≥30
Fiber Type	Input&Output	-	50/125um or 62.5/125um MM Fiber
		-	50/125um MM OM3 Fiber
		-	105/125um MM Fiber
	ASE Guide Out (Y/X Type)	-	Same Fiber
Fiber Tensile Load		N	5
Max. Optical Power (CW, ASE+Signal)		mW	300
Operating Temperature		°C	0~50
Storage Temperature		°C	-40~85
Package Dimension	Stainless Steel Tube (SST)	mm	∅5.5xL35
	Metal Box	mm	L120xW12xH10

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
 2. To add connectors, IL is 0.3dB higher, RL is 10dB lower.
 3. Specifications are tested at low order modes.
 4. Devices for higher optical power or with other type fiber or consigned fiber are also available.
 5. Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

FMBP-1078-NN(C) (C) (C) (C) -(C) C C NN -CC/CCC									
Bandwidth	ASE Type	ASE Iso	Fwd ASE Fiber	Bwd ASE Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
90~9nm	B=Backward T=Two-way Blank for Forward	I=High Isolation Blank for Standard	Y=Same Fiber N=None Blank for D Type	Y=Same Fiber Blank for None or D Type	M=Metal Box Blank for SST	5= 50/125um MM Fiber 6= 62.5/125um MM Fiber 3= OM3 MM Fiber A= 105/125um, NA=0.22 B=105/125um, NA=0.15	B= Bare fiber L= Loose Tube 2= 2mm Cable 3= 3mm Cable	05=0.5m 10=1.0m 15=1.5m 20=2.0m	N=Without Connector FC/APC=FC/APC Connector LC/PC=LC/PC Connector SC/UPC=SC/UPC Connector