

## 1021nm High Power PM Bandpass Filter

### FEATURES

- ☑ High Isolation
- ☑ Low Insertion Loss
- ☑ High Reliability and Stability
- ☑ Various Bandwidth
- ☑ High Optical Power

### APPLICATIONS

- ☑ Broadband Systems
- ☑ Optical Amplifying Systems
- ☑ Telecommunication Networks
- ☑ Laser Systems
- ☑ Research Labs



### SPECIFICATIONS

Parameters	Unit	Standard	High ER Type
Center Wavelength	nm	1021	
Min. Pass Band Width @ 0.5dB	nm	6.0	
Insertion Loss over Pass Band Wavelength	dB	≤1.2	≤1.4
Stop Wavelength (ASE)	nm	1000~1015&1027~1100	
Stop Wavelength (ASE) Standard	dB	≥25	
Isolation High Isolation	dB	≥45	
ASE Direction	-	F: Forward, B: Backward, T: Two-way	
Configuration	-	D: 2-port, Y: 3-port, X: 4-port	
Optical Return Loss	dB	≥50	
Extinction Ratio	dB	≥18	≥20
Fiber Type	Input&Output	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L) 10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W) 20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)
	ASE Guide Out (Y/X Type)	-	Same Fiber, Corr. SM Fiber or MM Fiber
Fiber Tensile Load	N	5	
Max. Optical Power (CW, ASE+Signal)	W	1, 2, 3, 5, 10, 15, 20, 30, 40, 50, 60, 80, 100	
Max. ASE Optical Power (CW)	W	0.3, 0.5, 1, 2, 3, 4, 5, 10	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package Dimension	Stainless Steel Tube (SST)	mm	∅5.5x <sup>L</sup> 35 (≤5W); ∅6.0x <sup>L</sup> 50 (5~10W)
	Metal Box	mm	<sup>L</sup> 90x <sup>W</sup> 12x <sup>H</sup> 10 (>10W); <sup>L</sup> 120x <sup>W</sup> 12x <sup>H</sup> 10 (≤10W)

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
  2. To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  3. High ER type can only work in slow axis; Suggest to use Y/X type or H Box if blocked optical power is ≥1W.
  4. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
  5. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
  6. Package size may be different for different fiber type, optical power and configurations.

### ORDERING INFORMATION (PN)

FPBP-1021-NN(C)(C) (C) (C) (C) - HPNN -(NN) -(C) C C NN -CC/CCC												
Bandwidth	Type	ASE Type	ASE Iso	Fwd ASE Fiber	Bwd ASE Fiber	Optical Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
60~6nm	R=High ER	B=Backward	I=High	Y=Same Fiber	Y=Same Fiber	1= 1W	1= 1W	M=Metal Box	2=PM980Fiber	B= Bare fiber	05~0.5m	N=Without Connector
	Blank for	T=Two-way	Isolation	S=Corr. SM Fiber	S=Corr. SM Fiber	5= 5W	5= 5W	H=H Box	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	Standard	Blank for Forward	Blank for	N=None	A=105/125um Fiber	10=10W	10=10W	Blank for SST	Q=20/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
			Standard	Blank for D Type	Blank for None or D Type	20=20W	Blank for 300mW		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector