# 1600~1790nm High Power 1x3 PM Fused Splitter Module

#### **FEATURES**

### **APPLICATIONS**

■ Low Excess Loss

Optical Amplifier

Various Splitting Ratio

Optical Networks

Wide Passband

Power Monitoring

■ High Stability and Reliability

Fiber Sensor

■ Epoxy Free Optical Path

Lab

## **SPECIFICATIONS**

Parameter		Unit	1x3		
Center Wavelength		nm	1625, 1650, 1700, 1730, 1750, 1790		
Bandwidth		nm	+/-10		
Insertion Loss	Тур.	dB	5.6		
	Max.	dB	6.1		
Uniformity		dB	1.0		
Extinction Ratio		dB	≥18		
Optical Return Loss		dB	≥40		
Directivity		dB	≥45		
Fiber Type		-	PM1550 Panda Fiber or PM1950 Fiber (V)		
			10/130um PMDC Fiber (O)		
Fiber Tensile Load		N	5		
Max. Optical Power (CW)		W	1, 2, 3, 5, 10, 15, 20, 25, 30, 40, 50, 60, 80, 100		
Operating Temperature		°C	0~50		
Storage Temperature		°C	-40~85		
Package Dimension		mm	(L)160x(W)140x(H)10		

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

- 2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
- 3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
- 4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

## **ORDERING INFORMATION (PN)**

FPCM-	NNNN	- NxN	-HP NN	- C	С	NN	- CC/CCC
	Wavelength	Configuration	Optical Power	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
	1600=1600nm	1X3=1X3 Type	1- 1W	V= PM1950 Fiber	B= Bare fiber	05=0.5m	N=Without Connector
	1650= 1650nm		2= 2W	0=10/130 PMDC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	1700=1700nm		10=10W	<i>Blank</i> for PM1550 Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	1750=1750nm		30=30W		3= 3mm Cable	<b>20=</b> 2.0m	SC/UPC=SC/UPC Connector



