

915nm 1x6/2x6 PM Fused Splitter Module for Pulse Power

FEATURES

- Low Excess Loss
- Various Splitting Ratio
- Wide Passband
- High Stability and Reliability
- Epoxy Free Optical Path

APPLICATIONS

- Optical Amplifier
- Optical Networks
- Power Monitoring
- Fiber Sensor
- Lab

SPECIFICATIONS

Parameter	Unit	1x6/2x6
Center Wavelength	nm	915, 930, 940, 950
Bandwidth	nm	+/-10
Insertion Loss	Typ.	dB
	Max.	dB
Uniformity	dB	1.8
Extinction Ratio	dB	≥16
Optical Return Loss	dB	≥40
Directivity	dB	≥45
Fiber Type	-	PM850 Fiber or PM980 Panda Fiber (H) PM1060L Fiber (E) or 10/125um PMDC Fiber (O)
Fiber Tensile Load	N	5
Max. Average Optical Power	W	0.3, 0.5, 1, 2, 3, 5, 10, 15, 20, 25, 30, 40, 50, 60, 80, 100
Max. Peak Power for Pulse	kW	0.1, 1, 2, 3, 5, 10, 15, 20
Operating Temperature	°C	0~50
Storage Temperature	°C	-40~85
Package Dimension	mm	(L)160x(W)160x(H)10

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
 2. To add connectors, IL is 0.7dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
 4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

ORDERING INFORMATION (PN)

FPCM-	NNN	- NxN	-H NN	P NN	-(C)	C	NN	-CC/CCC
	Wavelength	Configuration	Average Power	Peak Power	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
	915-915nm	1X6=1X6 Type	03=300mW	01=100W	H=PM980 Fiber	B= Bare fiber	05=0.5m	N=Without Connector
	930-930nm	2X6=2X6 Type	1= 1W	1= 1kW	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	940-940nm		10= 10W	5= 5kW	O=10/125PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	950-950nm		30=30W	10=10kW	Blank for PM850 Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector