

## 975~1000nm PM Filter Coupler for Pulse Power

### FEATURES

- ▣ Low Excess Loss
- ▣ Various Splitting Ratio
- ▣ Wide Passband
- ▣ High Stability and Reliability
- ▣ Epoxy Free Optical Path

### APPLICATIONS

- ▣ Optical Amplifier
- ▣ Optical Networks
- ▣ Power Monitoring
- ▣ Fiber Sensor
- ▣ Lab



### SPECIFICATIONS

Parameter		Unit	1x2 Type				2x2 Type		
Center Wavelength		nm	975, 980, 990, 1000						
Bandwidth		nm	+/-20nm or customer specify						
Split Ratio		-	0.1:99.9	1:99	2:98	5:95	10:90	40:60	50:50
Tap Ratio		-	0.1%	1±0.5%	2±0.6%	5±1.2%	10%	40%	50%
Excess Loss	Max.	dB	1.2				1.4		
Uniformity	Max.	dB	0.8				1.0		
Extinction Ratio		dB	≥18						
Optical Return Loss		dB	≥50						
Fiber Type	Tap Port	-	Same Fiber, Corresponding SM Fiber or 50/125um Fiber						
	Thru Port	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L) 10/125um PMDC Fiber (O) or 15/130um PMDC Fiber (W) 20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)						
Work Mode	Standard	-	Can only work in Slow Axis						
	B Type	-	Can work both in Slow Axis and Fast Axis						
Fiber Tensile Load		N	5						
Max. Average Optical Power		W	0.3, 0.5, 1, 2, 3, 5, 10, 15, 20, 30, 50, 60						
Max. Peak Power for pulse		kW	0.1, 1, 2, 3, 5, 10, 15, 20						
Operating Temperature		°C	0~50						
Storage Temperature		°C	-40~85						
Package	Stainless Steel Tube (SST)	mm	∅5.5x <sup>L</sup> 35 (≤5W); ∅6.0x <sup>L</sup> 50 (5~10W)						
Dimension	Metal Box	mm	<sup>L</sup> 90x <sup>W</sup> 12x <sup>H</sup> 10 (>10W); <sup>L</sup> 120x <sup>W</sup> 12x <sup>H</sup> 10 (≤10W)						

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
  2. To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
  4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
  5. Package size may be different for different optical power fiber type and configurations.

### ORDERING INFORMATION (PN)

Wavelength	Split Ratio	Tap Port Fiber	Type	Work Mode	Average Power	Peak Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
975~975nm	001=0.1/99.9	P=Same Fiber	1-1x2	B=B Type	03=300mW	01=100W	M=Metal Box	2=PM980Fiber	B= Bare fiber	05=0.5m	N=Without Connector
980~980nm	05=5/95	S=Corr. SM Fiber	2=2x2	Blank for Standard	1=1W	1=1kW	Blank for SST	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
990~990nm	10=10/90	5=50/125um Fiber			10=10W	5=5kW	or >10W	Q=20/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
1000~1000nm	50=50/50				20=20W	10=10kW		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector