

975~1160nm 1x5 PM Filter Splitter Module

FEATURES

0

0

0

0

Low Excess Loss 0

Wide Passband

Various Splitting Ratio

Epoxy Free Optical Path

High Stability and Reliability

ÅPPLICATIONS

- **Optical Amplifier** 0
- **Optical Networks** 0
- 0 **Power Monitoring**
- Fiber Sensor 0
- 0 Lab



SPECIFICATIONS

Parameter	Unit	Value		
	nm	975, 980, 990, 1000		
Center Wavelength		1020, 1030, 1040, 1053, 1064		
		1070, 1080, 1092, 1103, 1120, 1150		
Bandwidth	nm	+/-20nm or customer specify		
Configuration	-	1x5		
Split Ratio	%	Even Split		
Insertion Loss	dB	≤9.4		
Uniformity	dB	≤1.5		
Extinction Ratio	dB	≥20		
Optical Return Loss	dB	≥50		
Working Mode	-	Can only work in Slow Axis		
		PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L)		
Fiber Type	-	10/125um PMDC Fiber (O) or 15/130um PMDC Fiber (W)		
		20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)		
Alignment	-	Slow Axis		
Fiber Tensile Load	Ν	5		
Maximum Optical Power (CW)	mW	300		
Operating Temperature	°C	0~50		
Storage Temperature	°C	-40~85		
Package Dimension	mm	^L 160x ^W 140x ^H 10		

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

2. To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.

3. The devices can only work in slow axis and fast axis is blocked.

4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

ORDERING INFORMATION (PN)

FPFM-	NNNN -	1X5 -	С	С	NN -	CC/CCC
	Wavelength		Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
	975-975nm		2-PM980Fiber	8 - Bare Fiber	<mark>05=</mark> 0.5m	N–Without Connector
	1030-1030nm		E=PM1060L Fiber	L= Loose Tube	10-1.0m	FC/APC=FC/APC Connector
	1064-1064nm		Q=20/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	1120-1120nm		R=25/250 PMDC Fiber	<mark>3=</mark> 3mm Cable	<mark>20-</mark> 2.0m	SC/UPC=SC/UPC Connector

