

1050nm PM BP Filter/Tap Hybrid

FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



SPECIFICATIONS

Parameters	Unit	Value	
Center Wavelength	nm	1050	
Min. Pass Band Width @ 0.5dB	nm	2.0, 11	
Excess Loss	dB	≤1.6	
Stop wavelength (ASE)	2nm Bandwidth	nm	1000~1046&1054~1120
	11nm Bandwidth	nm	1000~1039&1061~1120
Stop Wavelength (ASE) Isolation	dB	Standard: ≥25; High Isolation ≥45	
Tap Ratio	%	1+/-0.6%, 2+/-0.8%, 5+/-1.0%, 10%, 20%, 30%, 50%	
Tap Position	F Type	-	Tap is before Bandpass Filter, Y Type (3-port), Both axis working
	S Type	-	Tap is before Bandpass Filter, Y Type (3-port), Only Slow axis working
	B Type	-	Tap is after Bandpass Filter, Y Type (3-port), Only slow axis working
	X Type	-	Tap is after Bandpass Filter, 4-port, Only Slow axis working (Blocked Wavelength Guide Out)
Optical Return Loss	dB	≥50	
Extinction Ratio	dB	≥18	
Fiber Type	Input&Output	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L) 10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W) 20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)
	Tap Port or 4 th Port	-	Same Fiber, Corr. SM Fiber or MM Fiber
Fiber Tensile Load	N	5	
Max. Optical Power (CW)	mW	300	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package	Stainless Steel Tube (SST)	mm	∅5.5xL40 (≤5W); ∅6.0xL50 (5~10W)
Dimension	Metal Box	mm	L120xW12xH10 (≤10W)

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
 - To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 - Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

FPHB-1050-NN(C) NN (C) - C (C) - (C) C C NN - CC/CCC

Bandwidth	ASE Iso	Tap Ratio	Position	Tap Port Fiber	4th Port Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
20-2nm	I=High	01-1%	F=F Type	Y=Same Fiber	Y=Same Fiber	M=Metal Box	2=PM980Fiber	B=Bare fiber	05-0.5m	N=Without Connector
110-11nm	Isolation	05-5%	S=S Type	S=Corr. SM Fiber	S=Corr. SM Fiber	Blank for SST	E=PM1060L Fiber	L=Loose Tube	10-1.0m	FC/APC=FC/APC Connector
	Blank for	10-10%	X=X Type	S=50/125um Fiber	S=50/125um Fiber		Q=20/130 PMDC Fiber	2=2mm Cable	15-1.5m	LC/PC=LC/PC Connector
	Standard	50-50%	Blank for B Type		Blank for F/S/B Type		R=25/250 PMDC Fiber	3=3mm Cable	20-2.0m	SC/UPC=SC/UPC Connector

